

Lamp types for oscillators

Type	Rated Volts	Rated mA	Hot R ohms	note
unknown	1.5	15	100	"grain-of-rice"
375	3	15	200	midget flanged
2158	"	"	"	wire terminals
7375	"	"	"	bi-pin
2AS15	5	21	239	wire terminals
6022AS15	"	"	"	"
8022	"	"	"	sub-midget
84E	6.3	40	158	wire terminals
10AS	10	10	1000	"
9131C	"	"	"	bi-pin
344	10	14	714	midget flanged
1869	"	"	"	wire terminals
10CS	10	17	588	"
10ES	10	35	286	"
12ES	12	40	300	"
2174	"	"	"	"
18E	14	40	350	"
16CS	16	17	941	"
7220	18	26	692	"
24CS	24	17	1412	"
24B/WT	24	40	600	"
24ES	"	"	"	"
2176	"	50	480	"
6838	28	24	1167	"
28ES	28	40	700	"
28MB	"	"	"	min. bayonet
28PC	"	"	"	bi-pin
28PS	"	"	"	wire terminals
85E	"	"	"	"
327	"	"	"	midget flanged
1762 / 1764	"	"	"	wire terminals
1819	"	"	"	min. bayonet
2185	"	"	"	wire terminals
2187	"	"	"	"
1829	28	70	400	min. bayonet
1918	32	40	800	wire terminals
48D/WT	48	21	2286	"
48C/WT	"	35	1371	"
48ES	"	40	1200	"
48MB	"	50	960	min. bayonet
48PS	"	"	"	wire terminals
55C/WT	55	50	1100	"
1835	"	"	"	min. bayonet
60MB	60	50	1200	"
60PC	"	"	"	bi-pin
60PS	"	"	"	wire terminals
90MB	90	30	3000	min. bayonet
120MB	120	25	4800	"
120PS	"	"	"	wire terminals